

## WD-850A

### UHF Antenna Divider

- Provides diversity output for up to four receivers/tuner base units
- Multi-channel operation by combination with the MB-8N and WRU-8N or the MB-X6 and WRU-806B

- Cascade output can be used for an additional antenna-divider or receiver/tuner base unit
- Two pair of antenna input connectors for up to four AN-820A antennas to expand the operating area of a wireless microphone system

## Technical Specifications

Group heading	
Frequency range	470MHz - 862MHz
Channel distribution	Inputs: 2 pairs Outputs: 4 pairs
Input/output impedance	50 $\Omega$
Cascade output	1 pair
Power supply for antenna booster (supplied from antenna input connectors)	DC 9 V/OFF switchable
Power consumption	16 W

Dimensions (W x H x D)	482 x 44 x 300 mm (19 x 1 3/4 x 11 7/8 inches)
Mass	Approx. 4.6 kg (10 lb 2 oz)
RF muting (squellch) level	5 dB $\mu$ , 10 dB $\mu$ , 15 dB $\mu$ or OFF
Audio output level	-58 dBm at reference deviation
Audio output connector	SMC9-4S (Sony 4-pin) (2), balanced

### Supplied Accessories

	50 $\Omega$ BNC terminators (6)
--	---------------------------------