

WIRELESS INTERCOM SYSTEM WB-200 Series

PRELLIMINARY INFORMATION



NEW

WBP-210



WBP-212



SPECIFICATIONS WBP-212

- ◆ DUAL CHANNEL BELTPACK. MANAGEMENT APPLICATIONS
- ◆ SINGLE A, B or COMBINED A+B LISTENING.
- ◆ SINGLE A, B or COMBINED A+B TALK FUNCTION.
- ◆ "STAGE ANNOUNCE" FUNCTION. DIRECT PA MESSAGES.

COMMON SPECIFICATIONS

- ◆ DIGITAL. ENCRYPTED COMMUNICATIONS.
- ◆ LICENSE FREE FREQUENCY OPERATION.
- ◆ RANGE: 300 to 75 meters.
- ◆ DUAL INTERNAL DIVERSITY ANTENNAS
- ◆ MAIN BATTERY: LI-Ion. BATTERY LIFE 15 HOURS
- ◆ SECONDARY BATTERY: 1 X AA Alkaline. LIFE: 4-6 HOURS
- ◆ BATTERY CHARGING BY ALTAIR WBPC-210 CHARGER

- ◆ WBP-210 ONE CHANNEL BELTPACK
- ◆ WBP-212 DUAL CHANNEL MANAGER BELTPACK

Altair introduces the new WBP210 and WBP212 rugged belt packs, compatible with the WB200 Wireless Intercom. This new models are conceived for diverse extreme applications: live music performance, TV ENG, open air cinema takes and other outdoor applications requiring extended reliability.

New performances are incorporated to ease the use in stress conditions: Headset connector by standard size XLR-4 for a higher durability and compatibility, long life Li-Ion battery, secondary battery supply for emergency uncharged main batteries, keyboard lock to prevent inadvertent operations, bigger illuminated switch buttons, and many others.

Internal preset configurations, battery remaining time, coverage and another information is provided by a helpful color screen. General keyboard operation is enabled by direct keystrokes in both upper and front panels.

Other general specifications are maintained over the classic WBP-200/202 belt packs: internal dual diversity antennas, high listening level, number of belt packs per base station, coverage, etc. This new belt packs can be combined with the classic size WBP-200/202 on the same installation.

CHASSIS

Ruggedized, full 3 mm wall thickness ABS. Comfortable feel rubberised corners. Unbreakable beltclip. Enclosure Dimension: 145x95x35 mm.

SWITCHES AND CONNECTIONS

Upper panel:

- MIC on/off/ptt illuminated switch.
- Channel A/B selector, Stage Announce switches (WBP-212)
- Volume Up-Down controls (WBP-210)

Lower panel:

- Headset connector by XLR-4 and mini XLR-4.
- USB-B for battery charging and firmware updates.

Front panel

- Up-Down volume controls. Display configuration keys.
- Illuminated CALL switch
- ON/OFF illuminated switch
- LCD color screen allowing preset configurations.



EQUIPOS EUROPEOS ELECTRONICOS

www.altairaudio.com