

AD-12 Passive Antenna Divider | Combiner

Key Features

- The AD-12 can either divide a RF signal into 2 signal outputs or combine 2 signals into 1 signal output. Simultaneously, it transmits bias voltage to afterward boosters. This is an ideal accessory to set up antenna systems.
- The AD-12 adapts an isolated grounding design to avoid power noise from multi-receiver operation.

Technical Specifications

Frequency Range	470~1000MHz
Attenuation	3.5dB (typical)
Isolation	20dB (typical)
Impedance	50Ω
Max Volt/Current	50VDC 1.5A
Connector	TNC×3
Dimensions	90.3(W)×25(H)×55.4(D)mm 3.5(W)×1(H)×2.2(D)"
Weight	105g 3.7oz

