



## VS-161H (previously VS-161HDMI)

16x1 HDMI Switcher



The VS-161H is a high-performance switcher for HDMI signals. It reclocks and equalizes the signal and switches one of the 16 inputs to a single HDMI output.



## VS-161H (previously VS-161HDMI)

---

### FEATURES

---

- Max. Data Rate - 1.65Gbps.
- HDCP Compliant.
- HDTV Compatible.
- I-EDIDPro™ Kramer Intelligent EDID Processing™ - Intelligent EDID handling & processing algorithm ensures Plug and Play operation for HDMI systems.
- HDMI Support - HDMI (V.1.3 with Lip Sync, CEC).
- Dual Mode - PC and DVD Modes selectable by input.
- Flexible Control Options - Front panel, RS-232 (K-Router™ Windows®-based software is included), Ethernet & IR remote (included).
- Video Disconnect.
- Front Panel Lockout.
- Kramer Equalization & re-Klocking™ Technology - Rebuilds the digital signal to travel longer distances.
- Worldwide Power Supply - 100-240V AC.
- Standard 19" Rack Mount Size - 1U. Rack "ears" included.

### TECHNICAL SPECIFICATIONS

---

INPUT:	16 HDMI Connectors.
OUTPUT:	1 HDMI Connector.
BANDWIDTH:	Supports up to 1.65Gbps bandwidth per graphic channel.
COMPLIANCE WITH HDMI STANDARDS:	Supports HDMI 1.2 and HDCP.
RESOLUTION:	Up to UXGA; 1080p, deep color.
POWER SOURCE:	100-240V AC; 50/60Hz, 22VA.
CONTROLS:	Front panel buttons, infra-red remote control transmitter, RS-232, Ethernet.
DIMENSIONS:	19" x 7" x 1U W, D, H, rack mountable.
WEIGHT:	2.5kg (5.5lbs) approx.
ACCESSORIES:	Power cord.
OPTIONS:	Kramer HDMI cables.