



XE-21C

2x1 Component Video Mechanical Switcher



The XE-21C is a high performance switcher for component video signals. It switches one of two inputs to a single output.

FEATURES

- High Bandwidth - 980MHz (-3dB).
- HDTV Compatible.
- Mechanical (Passive) Switching - No power required.
- Input/Output - RCA Connectors.
- Compact Kramer TOOLS™ - 3 units can be rack mounted side-by-side in a 1U rack space with the optional RK-3T rack adapter.



XE-21C

TECHNICAL SPECIFICATIONS

INPUTS: 2 component video (Y, PB, PR, or Y, U, V), 1Vpp/75Ω on RCA connectors.
OUTPUT: 1 component video (Y, PB, PR, or Y, U, V), 1Vpp/75Ω on RCA connectors.
BANDWIDTH (-3dB): 750MHz.
DIFF. GAIN: 0.03%.
DIFF. PHASE: 0.03Deg.
K-FACTOR: <0.05%.
S/N RATIO: 73dB weighted.
CONTROL: Input selector button.
COUPLING: DC.
POWER SOURCE: No power needed.
DIMENSIONS: 12cm x 7.5cm x 2.5cm (4.7" x 0.98" x 2.95"), W, D, H.
WEIGHT: 0.3kg (0.66lbs).
ACCESSORIES: Mounting bracket.

