



XE-21X

2x1 Computer Graphics Video Mechanical Switcher



Compatible with HDTV component video signals when used with a breakout cable such as the Kramer C-GM/3RVF.



The XE-21X is a high-performance switcher for computer graphics video signals with resolutions up to and exceeding UXGA. It switches one of two inputs to a single output.

FEATURES

- High Bandwidth - 430MHz (-3dB).
- HDTV Compatible.
- Mechanical (Passive) Switching - No power required.
- Bidirectional Operation - Can be used as a 2x1 switcher (2 inputs, 1 output) or a 1x2 switcher (1 input, 2 outputs).
- Compact Kramer TOOLST™ - 3 units can be rack mounted side-by-side in a 1U rack space with the optional RK-3T rack adapter.



XE-21X

TECHNICAL SPECIFICATIONS

INPUTS: 2 computer video graphics with resolution up to UXGA on 15-pin HD connectors.
OUTPUT: 1 computer video graphics with resolution up to UXGA on a 15-pin HD connector.
BANDWIDTH (-3dB): 430MHz.
DIFF. GAIN: 0.02%.
DIFF. PHASE: 0.02Deg.
K-FACTOR: <0.05%.
S/N RATIO: 73dB.
COUPLING: DC.
CROSSTALK: -57dB.
POWER SOURCE: No power needed.
DIMENSIONS: 12cm x 7.5cm x 2.5cm (4.7" x 0.98" x 2.95") W, D, H.
WEIGHT: 0.3kg (0.66lbs).
ACCESSORIES: Mounting bracket.

