



RF+ Receiver

The RF+ Receiver is our newest addition in TurningPoint compatible receivers. No driver installation allows for easy implementation. The radio frequency technology allows for a 200 foot range and does not need a "line of sight" with the ResponseCard keypads. The approximate size of a thumb drive, it doesn't require the hassle of cables and is easy to transport from room to room or class to class. With 4 gigabytes of storage, you can collect and store up to 1000 responses at once. For use with TurningPoint assessment software and ResponseCard RF, ResponseCard RF LCD and ResponseCard NXT clickers.



Specifications

Size & Weight:

- Height: 3.29 inches (83.5 mm)
- Width: 0.9 inches (22.8 mm)
- Depth: 0.36 inches (9.2 mm)
- Weight: 0.4 ounce (11 grams)

Range:

- 200 ft range*

Power and Power Management:

- Powered by USB

Storage Capacity:

- 4 GB

Hardware Capacity:

- 1000 ResponseCards

Software Compatibility:

PC Products

- TurningPoint 5.0
- TurningPoint 4.5
- TurningPoint AnyWhere 3.2
- TurningKey 1.4
- RemotePoll 1.5

Mac Products

- TurningPoint 5.0
- TurningPoint AnyWhere 3.1
- TurningKey 1.3

Input Device Compatibility:

- ResponseCard RF
- ResponseCard RF LCD
- ResponseCard NXT
- ResponseCard XR

*Actual performance may vary depending on polling environment and other equipment



**Turning
Technologies**

Main: +31 (0) 85 4011 040
www.TurningTechnologies.com